

3 Way Splitter 'F' Type 5-2400MHz

Power Pass All Ports

17MM-DM03Q



For the Best

Features and Benefits

- » Foxtel Approved (F30938)
- » Suitable for both Satellite/TDT & FTA
- » DC power pass all ports
- » 10dB extra screening with soldered back
- » Frequency range 5-2400MHz
- » Also available in 50 pack (17MM-DM03QB)



Splitters and Taps

Matchmaster has a premium range of RF Splitters & Taps ranging from 1 Way through to 8 Way. We cater for both Terrestrial and Satellite frequencies with both Single Port AC/DC and All Port DC Power Pass products available.



17MM-DM03Q Specifications

	Frequency	
Insertion Loss	5-40MHz	8.2 to 6.0dB
	40-470MHz	6.0dB
	470-1000MHz	6.0 to 7.5dB
	1000-1750MHz	7.5 to 8.5dB
	1750-2150MHz	8.5 to 9.0dB
Return Loss	2150-2400MHz	9.0 to 10.5dB
	5-40MHz	≥10dB
	40-470MHz	≥10dB
	470-1000MHz	≥10dB
	1000-1750MHz	≥10dB
Isolation	1750-2150MHz	≥10dB
	2150-2400MHz	≥10dB
	5-40MHz	≥22dB
	40-1000MHz	≥23dB
DC Power Passing	1000-1750MHz	≥23dB
	1750-2400MHz	≥23dB
	from all output to input	Max. 500mA